

Quantum Computing - Final project

Solving satisfiability problems using Grover's Algorithm

Grover's algorithm is a quantum algorithm for unstructured search that finds with high probability the input to a black box that produces a particular output value. The canonical application of the algorithm is the problem of searching for an element in an unstructured array of elements. It is known that for an array of elements, Grover's algorithm finds the element in $\mathcal{O}(\sqrt{N})$ steps, leading to a quadratic improvement when compared with the classical search.

The black box can be considered a function. Grover's algorithm can be used to find an input or multiple inputs that produce a particular output. If a black box has r inputs that produce the desired output, Grover's algorithm finds one of these inputs in $\mathcal{O}(\sqrt{N/r})$ steps.

A Boolean satisfiability problem determines if a Boolean formula is satisfied, i.e. evaluates TRUE given a specific assignment of its binary variables. If this is the case, the formula is called satisfiable. On the other hand, if no such assignment exists, the function expressed by the formula is FALSE for all possible variable assignments, and the formula is unsatisfiable.

$$f(v_1, v_2, v_3) = (\neg v_1 \vee \neg v_2 \vee \neg v_3) \wedge (v_1 \vee \neg v_2 \vee v_3) \wedge (v_1 \vee v_2 \vee \neg v_3) \wedge (v_1 \vee \neg v_2 \vee \neg v_3) \wedge (\neg v_1 \vee v_2 \vee v_3)$$

Equation 1: Example of boolean formula with five clauses with three literals each - 3-SAT

The Boolean formula presented in Equation 1 is an example of a 3-SAT problem i.e. each clause has three literals. The goal is to find an assignment for each literal such that the function evaluates TRUE. Such a problem can be seen as a search problem, where the solution is the assignment where the Boolean formula is satisfied.

Keep in mind that the algorithm will start with a uniform superposition of all possible assignments. The oracle will be composed by gates that evaluate each clause and invert the amplitude of assignments that validate each clause. Hint: Multi control Toffoli gate.

○ Tasks:

- Design a solvable 3-SAT boolean formula.
- Implement Grover's algorithm for solving the satisfiability problem.
- Assess the quality of the solution employed by the quantum algorithm.

- Study the complexity associated with the algorithm applied to your problem, i.e. the optimal number of Grover iterations needed to reach a solution.

○ *References:*

- Satisfiability with Grover - <https://qiskit.org/textbook/ch-applications/satisfiability-grover.html>
- Grover's algorithm - Qiskit - <https://qiskit.org/textbook/ch-algorithms/grover.html>